

# Emerg-Power Systems IPS

## Single phase series



### Features

- 98% efficient at full load
- PWM/IGBT technology
- Self-testing/Self-diagnostic
- User programmable with password protection
- Standard input circuit breaker
- Standard normally off and on output
- RS232 communication port
- Micro-processor controlled
- Automatic event and alarm log
- 90 min. standard run time
- Generator compatibility
- Electronic and magnetic ballast compatible
- Custom voltages available
- Automatic event, test and alarm log
- LCD display
- Reduced footprint (stackable cabinets)
- Maintenance free standard batteries
- Forced air cooling during emergency mode only

UL listed to UL 924. Meets NFPA101, NFPA70, NFPA 110, OSHA, UBC, SBCCI. N.Y City approved.



### Electrical/mechanical characteristics<sup>4</sup> (data provided for standard lead calcium batteries)<sup>1,4</sup>

Power rating <sup>1</sup> VA= W	Effic. at full load %	Max. input current (A)		Heat loss in normal mode (BTU/HR)	Batt. VDC	Batt. A	No. of Batt.	UPS cabinet dimensions			Battery cabinet dimensions <sup>2,3</sup>			No. of batt. cab.	Batt. cab. weight lbs	UPS cab. weight lbs	Batt weight lbs	Total system weight lbs
		120V	277V					W"	H"	D"	W"	H"	D"					
1.5	98	16	7	102	48	39	4	30	47	25	N/A	N/A	N/A	N/A	N/A	250 lbs	296 lbs	546 lbs
2.25	98	24	11	153	72	38	6	30	47	25	N/A	N/A	N/A	N/A	N/A	265 lbs	444 lbs	709 lbs
3	98	32	14	204	96	38	8	30	47	25	N/A	N/A	N/A	N/A	N/A	295 lbs	592 lbs	887 lbs
3.75	98	39	17	255	120	37	10	30	47	25	N/A	N/A	N/A	N/A	N/A	305 lbs	740 lbs	1045 lbs
5	98	50	22	340	144	40	12	30	47	25	N/A	N/A	N/A	N/A	N/A	315 lbs	888 lbs	1203 lbs
6	98	63	27	408	180	40	15	30	47	25	30	47	25	1	210 lbs	350 lbs	1110 lbs	1670 lbs
8	98	84	36	544	240	39	20	30	47	25	30	47	25	1	232 lbs	375 lbs	1480 lbs	2087 lbs
10	98	105	45	680	144	82	24	30	47	25	30	47	25	1	420 lbs	435 lbs	1776 lbs	2631 lbs
12.5	98	131	57	850	180	82	30	30	47	25	30	47	25	2	420 lbs	465 lbs	2220 lbs	3105 lbs
16.7	98	174	76	1136	240	80	40	30	47	25	30	47	25	2	464 lbs	530 lbs	2960 lbs	3954 lbs

<sup>1</sup>System capacity can be upgraded in the field up to 2000VA by adding more battery cabinets. Re-programming required by factory service technician.

<sup>2</sup>Batteries are installed in separate modular cabinets

<sup>3</sup>Battery cabinets are stackable. Must be installed under the electronics cabinet

<sup>4</sup>Special voltages can change the size, weight or number of cabinets

### How to order

Input voltage <sup>1</sup>	Battery type	VA/W rating	System type	Output voltage <sup>2</sup>	Run time <sup>3</sup>	Input breaker	RS232 port	Output breakers <sup>4</sup>	Options <sup>5</sup>
120	SG= Sealed lead- calcium	1500	-IPS	-120	-90	-ICB	RS232	-OCBxxxx= No trip alarm <sup>4</sup>	-20Y= 20 yr sealed batteries
208		2250		-277					-12HR= 12 hr fast recharge
240		3000		-208					-MOD= External modem
277		3750		-120/140					-FAX= Fax modem
		5000		-120/277					-BPR= Bypass relays
		6000							-SEIS= Seismic mounting
		8000							-ZONEM= Zone monitoring
		10000							-BSTM= Battery cycle warranty monitor
		12500							
		16700							

Example: 277SG6000-IPS-277-90-ICB-RS232-OCB0420-DCS-20Y

<sup>1</sup>Special voltages may change the size, weight or number of cabinets

<sup>2</sup>Special voltages may change the size, weight or number of cabinets

<sup>3</sup>Other run times available

<sup>4</sup>Max. 12 unsupervised single pole positions or 8 with trip alarm. For more output breakers please consult factory.. See page 159 for output breaker details

<sup>5</sup>See page 159 for options description

<sup>6</sup>External bypass switch is not compatible with integrated output circuit breakers.

Input/output voltage has to be the same

## Specifications

### General

#### Design

- Stand-by. PWM inverter type utilizing IGBT technology with 50ms transfer time.

#### Control

- Microprocessor controlled, 2 x 20-character display with touch pad controls & functions
- 5 LED indicators & alarm with ring-back feature

#### Metering

- Input and output voltage, battery voltage, battery and output current, output VA, temperature, inverter wattage

**Communications** Optional RS-232 port (DB9)

### Electrical input

#### Voltage

120 or 277VAC, 1-phase 2-wire, +10%/-15%  
Contact factory for all other voltage.

#### Input power walk-in

Limiting inrush current to less than 125%,  
10 times for 1 line cycle

**Input frequency** 60Hz, +/-3Hz, available upon request

**Protection** Input circuit breaker

**Harmonic distortion** <10%

**Power factor** 0.5 lag/lead

### Electrical output

**Voltage** 120 or 277VAC, 1-phase 2-wire  
Contact factory for all other voltage

#### Static voltage

- Load current change +/-2%, battery discharge +/-12.5%

#### Dynamic voltage

- +/-2% for +/-25% load step change
- +/-3% for a 50% load step change, recovery within 3 cycles

**Harmonic distortion** <3% THD for linear load

**Output frequency** 60Hz +/- 0.05Hz during emergency mode

**Load power factor** 0.5 lag to 0.5 lead

**Inverter overload** 115% for 10 minutes, 150% for 16 line cycles

**Protection** Optional distribution circuit breaker

**Crest factor** 2.8

### Environmental conditions

#### Storage/transport

- -4°F to 158°F (-20°C to 70°C) without batteries
- 0°F to 104°F (-18°C to 40°C) with batteries  
(max. 3 months at 104° F (40° C))

#### Operating temperature

System operates safely from 32°F to 104°F (0°C to 40°C) but optimum operation is between 68° F and 86° F (20°C to 30°C). Battery performance can be affected by temperature

**Altitude** <10,000 feet (above sea level) without de-rating

**Relative humidity** 0 to 95% non-condensing

**Audible noise** Audible noise 45 dBA @ 1m from surface  
in emergency mode

### Cabinets

Modular design, freestanding NEMA Type 1 steel cabinets powder coated for corrosion and scratch resistance. Front access design through hinged lockable doors requires only 39" front clearance and 12" top clearance. Cabinets are stackable if required to further reduce the footprint. Top and left side conduit entry with knockouts.

### Inverter

Using IGBT/PWM technology the inverter converts DC voltage supplied by the batteries to AC voltage of a precise stabilized amplitude and frequency, suitable for most sophisticated electrical equipment. True sinusoidal output waveform with very low distortion (less than 3% for linear loads). Overload capability of up to 150% for 12 line cycles.

### Charger

Fully automatic, temperature compensated, microprocessor controlled charger recharges fully discharged batteries in maximum 24 hours at nominal AC input voltage. AC input current limiting and over-voltage protection included.

### Battery

System is provided standard with 10 year, maintenance free, sealed valve regulated, front terminals Lead-Calcium batteries. 20 year sealed Lead-Calcium battery also available. 90 min. standard discharge time at full load under normal operating temperature. Low voltage disconnect protection included. No special ventilation required.

### Self-diagnostics

Automatic self tests consist of a 5-minute monthly and 90-minute annual function. The front-mounted control panel includes 5 LED indicators, a 2-line 20-character LCD display, a keypad to control and monitor the internal operation of the system. This allows the operator to easily "watch" system functions as they occur and check on virtually any aspect of the system's operation. Standard RS232 diagnostic interface

### Alarms

High/low battery charger voltage, high/low AC Input Voltage, Near low battery, low battery, load reduction fault, output overload, high ambient temperature, inverter fault, output fault, optional output circuit breaker trip

### Optional features

Output circuit breakers, output trip alarms, 20 years sealed batteries, 12 hours fast recharge, internal/external maintenance bypass switch, remote meter panel, remote summary alarm panel, summary alarm dry form C contact, inverter on dry contacts, fax modem, bypass relays, auto dialer, seismic mounting.

### Factory start-up

Includes one additional year of warranty. See warranty conditions

### Warranty

 (full limited warranty conditions available upon request)

Limited manufacturer warranty is one-year, parts and labor, for system electronics or two-year with factory start-up program. Battery warranty is one year full plus 9 years pro-rata for a total of 10 years, under normal operating conditions. System must be put in service within 6 months from ship date in order to validate warranty  
2-Consult factory for other type batteries than the standard one.

### Single line diagram

